

What is claimed is:

- Sub
A1
1. A charge pump, comprising:
a plurality of phase generators;
first and second preboot capacitors coupled to the plurality of phase generators;
first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and
first and second gating devices coupled to the first and second main pump capacitors, respectively.
 2. The charge pump of claim 1, wherein the first and second main pump capacitors ^{are} prebooted to a first predetermined level by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved ^s to a second predetermined level in response to the plurality of phase generators during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level in response to the plurality of phase generators during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and a nd second gating devices, during the first and second phases, respectively.
 3. A charge pump, comprising:
a plurality of phase generators;
first and second preboot capacitors coupled to the plurality of phase generators;
first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and
first and second gating devices coupled to the first and second main pump capacitors, respectively; and

wherein the first and second main pump capacitors is prebooted to a first predetermined level by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved to a second predetermined level in response to the plurality of phase generators during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level in response to the plurality of phase generators during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and a second gating devices, during the first and second phases, respectively.

4. The charge pump of claim 3, wherein the plurality of phase generators further comprises:
- a primary phase generator;
 - a secondary phase generator coupled to the primary phase generator;
 - ^{said} first and second preboot capacitors coupled to the primary phase generator;
 - and
 - ^{said} first and second main pump capacitors coupled to the secondary phase generator, and the first and second preboot capacitors, respectively.

5. A charge pump, comprising:
- an oscillator to generate a first and a second phase during a phase cycle;
 - a primary phase generator coupled to the oscillator;
 - a secondary phase generator coupled to the primary phase generator;
 - first and second preboot capacitors coupled to the primary phase generator;
 - first and second main pump capacitors coupled to the secondary phase generator, and the first and second preboot capacitors, respectively;
 - first and second gating devices coupled to the first and second main pump capacitors, respectively; and

wherein the first and second main pump capacitors is prebooted to a first predetermined level by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved to a second predetermined level in response to the primary phase generator during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level in response to the secondary phase generator during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and a second gating devices, during the first and second phases, respectively.

6. The charge pump of claim 5, further including a power source, wherein the power source includes an output voltage approximately in the range of about 1 to 2.5 volts.

7. The charge pump of claim 5, wherein the primary phase generator comprises:

an inverter, coupled to the oscillator to receive an input signal from the oscillator based on the phase cycle and providing output signals which are 180 degrees out of phase; and

cross coupled gates coupled to the inverter to receive the output signals from the inverter and outputting signals that are non-overlapping and crossing around high points of their signals during the first and second phases, respectively, and further outputting signals that are non-overlapping and crossing around low points of their signals during the first and second phases, respectively.

8. The charge pump of claim 5, wherein the secondary phase generator comprising a delay circuit coupled to the primary phase generator, including an input receiving signals that are non-overlapping and crossing around high points of their signals from the primary phase generator, and providing an output signal similar to the input signal, and having a predetermined delay from the input signal.

9. The charge pump of claim 8, wherein the predetermined delay is approximately in the range of about 10 to 30 nanoseconds.

Sub
CG
10. The charge pump of claim 8, wherein the first and second preboot capacitors coupled to the primary phase generator to receive input signals that are non-overlapping and crossing around high points and low points of their signals, and providing an output signal to preboot the first and second main capacitors to a first predetermined level during the first and second phases, respectively.

11. The charge pump of claim 10, wherein the first predetermined level is approximately in the range of about 1 to 5 volts.

Sub
E'
12. The charge pump of claim 10, further comprising first and second precharge capacitors coupled to the primary phase generator and the first and second main pump capacitors, respectively, including an input receiving the signals that are non-overlapping and crossing around high points of their signals and providing an output signal to precharge the first and second main capacitors to a second predetermined level during the first and second phases, respectively.

13. The charge pump of claim 12, wherein the second predetermined level is approximately in the range of about 1 to 5 volts.

14. The charge pump of claim 12, wherein the first and second precharge capacitors further comprising transistors to precharge the first and second precharge capacitors.

15. The charge pump of claim 14, wherein the first and second main pump capacitors coupled to the secondary phase generator, and the first and second precharge capacitors, respectively, including an input receiving the delayed signal from the secondary phase generator to move the second predetermined level to a

third predetermined level, and dumping an output during the first and second phases, respectively.

16. The charge pump of claim 15, wherein the third predetermined level is approximately in the range of about 1 to 5 volts.

17. The charge pump of claim 15, wherein the first and second gating devices coupled to the first and second main pump capacitors, including an input receiving the dumped signal from the first and second main pump capacitors and an output outputting a charge to an external load.

18. The charge pump of claim 15, wherein the outputting charge is approximately in range of about 1.5 to 5 volts.

19. A charge pump, comprising:
an oscillator to generate a first and a second phase during a phase cycle;
a primary phase generator coupled to the oscillator;
a secondary phase generator coupled to the primary phase generator;
first and second preboot capacitors coupled to the primary phase generator;
first and second main pump capacitors coupled to the secondary phase generator, and the first and second preboot capacitors, respectively;
first and second gating devices coupled to the first and second main pump capacitors, respectively; and
wherein the first and second main pump capacitors is prebooted to a first predetermined level of approximately in the range of about 1 to 5 volts by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved to a second predetermined level of approximately in the range of about 1 to 5 volts in response to the primary phase generator during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level of approximately in the

range of about 1 to 1.5 volts in response to the secondary phase generator during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and a second gating devices, during the first and second phases, respectively.

20. A charge pump, comprising:
- an oscillator to generate a first and a second phase during a phase cycle;
 - a primary phase generator coupled to the oscillator further includes;
 - an inverter, coupled to the oscillator to receive an input signal from the oscillator based on the phase cycle and providing output signals which are 180 degrees out of phase; and
 - cross coupled gates coupled to the inverter to receive the output signals from the inverter and outputting signals that are non-overlapping and crossing around high points of their signals during the first and second phases, respectively, and further outputting signals that are non-overlapping and crossing around low points of their signals during the first and second phases, respectively;
 - a secondary phase generator coupled to the primary phase generator receives the signals that are non-overlapping and crossing around high points of their signals from the primary phase generator;
 - first and second preboot capacitors coupled to the primary phase generator receives the signals that non-overlapping and crossing around high points and low points of their signals from the primary phase generator;
 - first and second main pump capacitors coupled to the secondary phase generator, and the first and second preboot capacitors, respectively;
 - first and second gating devices coupled to the first and second main pump capacitors, respectively; and
 - wherein the first and second main pump capacitors is prebooted to a first predetermined level by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved to a

second predetermined level in response to the primary phase generator during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level in response to the secondary phase generator during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and a second gating devices, during the first and second phases, respectively.

21. A charge pump, comprising:
- an oscillator to generate a first and a second phase during a phase cycle;
 - first and second primary phase generators coupled to the oscillator;
 - first and second secondary phase generators coupled to the first and second primary phase generators, respectively;
 - first and second preboot capacitors coupled to the first and second primary phase generators, respectively;
 - a first main pump capacitor coupled to the first secondary phase generator, and the first preboot capacitor;
 - a second main pump capacitor coupled to the second secondary phase generator, and the second preboot capacitor;
 - a first and second p-channel gates coupled to the first and second main pump capacitors, respectively;
 - wherein the first main pump capacitor is prebooted to a first pre-determined level by the second preboot capacitor during the first phase, wherein the first pre-determined level moved to a second pre-determined level during the second phase in response to the first primary phase generator, wherein the second predetermined level moved to a third predetermined level in response to the first secondary phase generator, and wherein the third predetermined level dumped to a first p-channel gate during the first phase; and
 - wherein the second main pump capacitor is prebooted to a first pre-determined level by the first preboot capacitor during the second phase, wherein the first predetermined level moved to a second pre-determined level during the first

phase in response to the second primary phase generator, wherein the second predetermined level moved to a third predetermined level in response to the second secondary phase generator, and wherein the third predetermined level dumped to a second p-channel gate during the second phase.

22. A charge pump circuit, comprising:

a phase generator to generate a first and a second phase during a phase

cycle;

a primary phase generator, coupled to the phase generator, wherein the primary phase generator includes a first and a second phase generator to generate a first and a second phase signal that are non-overlapping and crossing each other substantially around their high points during the phase cycle, wherein the primary phase generator further generates a third and a fourth phase signal that are non-overlapping and crossing around their low points during the phase cycle, and wherein the primary phase generator further generates a seventh and a eighth phase signal;

a secondary phase generator, coupled to the primary phase generator, wherein the secondary phase generator includes a first and a second secondary phase generator to generate a fifth and sixth phase signal similar to first and second phase signal, and including a predetermined delay from the first and second phase signal;

a first and a second main energy storing device;

a first and a second pre-boosting stage, coupled to the first and second primary phase generators respectively, wherein the first and second pre-boosting stages boosts the first and second main energy storing devices to a first predetermined boost level during the first and second phases respectively; and

a first and a second pre-charging stage, coupled to the first and second main energy storing devices, wherein the first and second pre-charging stages further boost the first and second main energy storing devices to a second predetermined boost level during the first and second phases respectively, wherein the first and

second main energy storing devices are further boosted to a third predetermined boost level by the fifth and sixth phase signals to allow the first and second main energy storing devices to output a desired level of a high-voltage signal during the first and second phases.

23. A two-phase integrated circuit charge pump, comprising:

an oscillator, where the oscillator generates an oscillating signal during a phase cycle including a first and a second phase;

a primary phase generator, coupled to the oscillator, wherein the primary phase generator generates a first phase signal and a second phase signal that are non-overlapping and crossing each other around high points of their signals during a phase cycle, further the primary phase generator generates a third phase signal and a fourth phase signal that are non-overlapping and crossing each other around low points of their signals during every phase cycle, and further the primary phase generator generates a seventh phase signal and an eighth phase signal;

a secondary phase generator, coupled to the primary phase generator, wherein the secondary phase generator receives the first and second phase signals and generates a fifth phase signal and a sixth phase signal that are non-overlapping and crossing each other around high points of their signals during a phase cycle and includes a predetermined delay from the first and second phase signals;

a first and second pre-boot precharge capacitors, coupled to the primary phase generator, wherein the first and second pre-boot precharge capacitors receive the third and fourth phase signals from the primary phase generator during the first and second phases respectively;

a first and second pre-boot capacitors, coupled to the primary phase generator and the first and second pre-boot precharge capacitors respectively, receives the first and second phase signals from the primary phase generator respectively, and wherein the first and second pre-boot precharge capacitors pre-charges the first and second pre-boot capacitors to a pre-determined level during the first and second phases respectively;

cont
Sub
D6

[illegible][illegible][illegible][illegible][illegible]

a delay element, coupled to the primary phase generator, receives the first and second phase signals and generates a fifth phase signal and a sixth phase signal that are non-overlapping and crossing each other around high points of their signals during every phase cycle and includes a predetermined delay from the first and second phase signals;

a first and second pre-boot precharge circuitry, coupled to the primary phase generator, receives the third and fourth signals from the primary phase generator during a first and second phases respectively;

a first and second pre-boot circuitry, coupled to the primary phase generator and the first and second pre-boot precharge capacitors respectively, receives the first and second phase signals from the primary phase generator respectively, and where the first and second pre-boot precharge circuitry pre-charges the first and second pre-boot capacitors to a pre-determined level during the first and second phases respectively;

a first and second main pump precharge circuitry, coupled to the primary phase generator receives the seventh and eighth phase signals from the delay element during the first and second phases respectively;

a first main pump circuitry, coupled to the first main pump precharge circuitry, the second pre-boot circuitry, and the delay element, where the second pre-boot circuitry pre-boots the first main pump circuitry to a predetermined booted level during the first phase, further the first main pump precharge circuitry precharges the first main pump circuitry to a second pre-determined level during the second phase and further the first main pump circuitry receives the fifth phase signal from the delay element during the first phase, and where the first main pump circuitry goes to a third predetermined level and outputs a charge to a first p-channel gate during the first phase; and

Cond
Sub
D6

a second main pump circuitry, coupled to the second main pump precharge circuitry, the first pre-boot circuitry, and the delay element, where the first pre-boot circuitry pre-boots the second main pump to a predetermined booted level during the second phase, further the second main pump precharge circuitry precharges the second main pump circuitry to a second pre-determined level during the first phase, and further the second main pump circuitry receives the sixth phase signal from the delay element during the second phase, and where the second main pump circuitry goes to the third predetermined level and outputs the charge to a second p-channel gate during the second phase.

25. A charge pump circuit, comprising:

a phase generator to generate a first phase and a second phase, wherein the first phase is 180 degrees out of phase with respect to the second phase;

a primary phase generator, coupled to the oscillator, generates a first phase signal and a second phase signal that are non-overlapping and crossing each other around high points of their signals during every phase cycle (consisting of a first phase and a second phase), further the primary phase generator generates a third phase signal and a fourth phase signal that are non-overlapping and crossing each other around low points of their signals during every phase cycle, and further the primary phase generator generates a seventh phase signal and a eighth phase signal;

a secondary phase generator, coupled to the primary phase generator, receives the first and second phase signals and generates a fifth phase signal and a sixth phase signal that are non-overlapping and crossing each other around high points of their signals during every phase cycle and includes a predetermined delay from the first and second phase signals;

a first and second pre-boot precharge capacitors, coupled to the primary phase generator, receives the third and fourth signals from the primary phase generator during a first and second phases respectively;

a first and second pre-boot capacitors, coupled to the primary phase generator and the first and second pre-boot precharge capacitors respectively,

first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and

first and second gating devices coupled to the first and second main pump capacitors, respectively.

27. A memory device, comprising:

a plurality of phase generators;

first and second preboot capacitors coupled to the plurality of phase generators;

first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively;

first and second gating devices coupled to the first and second main pump capacitors, respectively; and

wherein the first and second main pump capacitors is prebooted to a first predetermined level by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved to a second predetermined level in response to the plurality of phase generators during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level in response to the plurality of phase generators during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and a second gating devices, during the first and second phases, respectively.

28. A semiconductor die, comprising:

a substrate; and

an integrated circuit supported by the substrate, wherein the integrated circuit comprises at least one memory device, further wherein the at least one memory device comprises:

a plurality of phase generators;

Cont
Sub
A4

first and second preboot capacitors coupled to the plurality of phase generators;

first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and

first and second gating devices coupled to the first and second main pump capacitors, respectively.

29. A semiconductor die, comprising:

a substrate; and

an integrated circuit supported by the substrate, wherein the integrated circuit comprises at least one memory device, further wherein the at least one memory device comprises:

a plurality of phase generators;

first and second preboot capacitors coupled to the plurality of phase generators;

first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and

first and second gating devices coupled to the first and second main pump capacitors, respectively.

30. A semiconductor die, comprising:

a substrate; and

an integrated circuit supported by the substrate, wherein the integrated circuit comprises at least one memory device, further wherein the at least one memory device comprises:

a plurality of phase generators;

first and second preboot capacitors coupled to the plurality of phase generators;

first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and

first and second gating devices coupled to the first and second main pump capacitors, respectively; and

wherein the first and second main pump capacitors is prebooted to a first predetermined level by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved to a second predetermined level in response to the plurality of phase generators during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level in response to the plurality of phase generators during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and a second gating devices, during the first and second phases, respectively.

31. A memory system, comprising:

a controller;

a command link coupled to the controller;

a data link coupled to the controller; and

a memory device coupled to the command link and the data link, wherein the memory device comprises:

a plurality of phase generators;

first and second preboot capacitors coupled to the plurality of phase generators;

first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and

first and second gating devices coupled to the first and second main pump capacitors, respectively.

Cont
Sub
A4

32. A memory system, comprising:
- a controller;
 - a command link coupled to the controller;
 - a data link coupled to the controller; and
 - a memory device coupled to the command link and the data link, wherein the memory device comprises:
 - a plurality of phase generators;
 - first and second preboot capacitors coupled to the plurality of phase generators;
 - first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively;
 - and
 - first and second gating devices coupled to the first and second main pump capacitors, respectively; and
 - wherein the first and second main pump capacitors is prebooted to a first predetermined level by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved to a second predetermined level in response to the plurality of phase generators during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level in response to the plurality of phase generators during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and second gating devices, during the first and second phases, respectively.
33. An electronic system, comprising:
- a processor; and
 - at least one memory device coupled to the processor, wherein the at least one memory device comprises:
 - a plurality of phase generators;

first and second preboot capacitors coupled to the plurality of phase generators;

first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and

first and second gating devices coupled to the first and second main pump capacitors, respectively.

34. An electronic system, comprising:

a processor; and

at least one memory device coupled to the processor, wherein the at least one memory device comprises:

a plurality of phase generators;

first and second preboot capacitors coupled to the plurality of phase generators;

first and second main pump capacitors coupled to the plurality of phase generators, and the first and second preboot capacitors, respectively; and

first and second gating devices coupled to the first and second main pump capacitors, respectively; and

wherein the first and second main pump capacitors is prebooted to a first predetermined level by the first and second preboot capacitors during the first and second phases, respectively, wherein the first predetermined level moved to a second predetermined level in response to the plurality of phase generators during the first and second phases, respectively, wherein the second predetermined level is moved to a third predetermined level in response to the plurality of phase generators during the first and second phases, respectively, and wherein the third predetermined level is dumped to the first and a second gating devices, during the first and second phases, respectively.

pre-charging the second main pump capacitor to the second pre-determined level during the first phase;

boosting the second main pump to the third pre-determined level during the second phase; and

outputting the second main pump charge to a second p-channel gate during the second phase.

37. A method of producing a pump supply voltage from an integrated circuit two phase charge pump, comprising:

recharging a pre-boot capacitor to a first pre-determined level during a first phase;

recharging a second pre-boot capacitor to the first pre-determined level during a second phase;

pre-charging a first main pump capacitor to a second pre-determined level during the second phase;

boosting the first main pump to a third pre-determined level during the first phase;

outputting the first main pump charge to a first p-channel gate during the first phase;

outputting the charge from the first p-channel gate to a V_{ccp} ;

pre-charging the second main pump capacitor to the second pre-determined level during the first phase;

boosting the second main pump to the third pre-determined level during the second phase;

outputting the second main pump charge to a second p-channel gate during the second phase; and

outputting the charge from the second p-channel gate to a V_{ccp} .

38. A method of producing a pump supply voltage from an integrated circuit two phase charge pump, comprising:

generating signals that are non-overlapping and crossing each other around high points of their signals;

generating signals that are non-overlapping and crossing each other around low points of their signals;

generating signals having a predetermined delay from the signals that are non-overlapping and crossing each other around high points;

recharging a first pre-boot capacitor to a first pre-determined level using the signals that are non-overlapping and crossing around the high points of their signals during a first phase;

recharging a second pre-boot capacitor to the first pre-determined level using the signals that are non-overlapping and crossing around the low points of their signals during a second phase;

pre-charging the first main pump capacitor to a second pre-determined level by the signals that are non-overlapping and crossing around the low points of their signals during the second phase;

inputting the signals having a predetermined delay to boost the first main pump to a third pre-determined level during the first phase;

outputting the first main pump charge to a first p-channel gate during the first phase;

outputting the charge from the first p-channel gate to a V_{ccp} ;

pre-charging the second main pump capacitor to the second pre-determined level by the signals that are non-overlapping and crossing around the low points of their signals during the first phase;

inputting the signals having a predetermined delay to boost the second main pump to the third pre-determined level during the second phase;

outputting the second main pump charge to a second p-channel gate during the second phase; and

outputting the charge from the second p-channel gate to a V_{ccp} .

Sub
D7

39. A method of producing a pump supply voltage from an integrated circuit two phase charge pump, comprising:

generating an oscillating signal;

generating a first and second phase signals that are non-overlapping and crossing each other around high points of their signals during every phase cycle from the oscillating signal by a primary phase generator;

generating a third and fourth phase signals that are non-overlapping and crossing each other around low points of their signals during every phase cycle from the oscillating signal by the primary phase generator;

generating a fifth and sixth phase signals having a predetermined delay from the first and second phase signals that are non-overlapping and crossing each other around high points from the first and second phase signals received from the primary phase generator by a secondary phase generator;

generating a seventh and eighth phase signals by the primary phase generator;

recharging a first pre-boot capacitor to a first pre-determined level using the first and third phase signals during the first phase;

recharging a second pre-boot capacitor to the first pre-determined level using the second and fourth phase signals during the second phase;

pre-booting a first main pump capacitor to the pre-determined boot level by the second pre-boot capacitor during the first phase;

pre-booting a second main pump capacitor to a pre-determined boot level by the first pre-boot capacitor during the second phase;

pre-charging the first main pump capacitor to a second pre-determined level by the seventh phase signal during the second phase;

inputting the fifth phase signal to boost the first main pump to a third pre-determined level during the first phase;

outputting the first main pump charge to a first p-channel gate during the first phase;

outputting the charge from the first p-channel gate to a V_{ccp} ;

pre-charging the second main pump capacitor to the second pre-determined level by the eight phase signal during the first phase;

inputting the sixth phase signal to boost the second main pump to the third pre-determined level during the second phase;

outputting the second main pump charge to a second p-channel gate during the second phase; and

outputting the charge from the second p-channel gate to a V_{ccp} .

40. A method of producing a pump supply voltage from an integrated circuit two phase charge pump, comprising:

generating an oscillating signal;

generating a first and second phase signals that are non-overlapping and crossing each other around high points of their signals during every phase cycle from the oscillating signal by a primary phase generator;

generating a third and fourth phase signals that are non-overlapping and crossing each other around low points of their signals during every phase cycle from the oscillating signal by the primary phase generator;

generating a fifth and sixth phase signals having a predetermined delay of approximately in the range of about 10 to 30 nanoseconds from the first and second phase signals that are non-overlapping and crossing each other around high points from the first and second phase signals received from the primary phase generator by a secondary phase generator;

generating a seventh and eighth phase signals by the primary phase generator;

recharging a first pre-boot capacitor to a first pre-determined level of approximately in the range of about 1 to 5 volts using the first and third phase signals during the first phase;

recharging a second pre-boot capacitor to the first pre-determined level of approximately in the range of about 1 to 5 volts using the second and fourth phase signals during the second phase;

cont
sub
D7

[illegible][illegible][illegible][illegible][illegible]

	1970	1969	1968	1967	1966	1965	1964	1963	1962	1961	1960	1959	1958	1957	1956	1955	1954	1953	1952	1951	1950	1949	1948	1947	1946	1945	1944	1943	1942	1941	1940	1939	1938	1937	1936	1935	1934	1933	1932	1931	1930	1929	1928	1927	1926	1925	1924	1923	1922	1921	1920	1919	1918	1917	1916	1915	1914	1913	1912	1911	1910	1909	1908	1907	1906	1905	1904	1903	1902	1901	1900	1899	1898	1897	1896	1895	1894	1893	1892	1891	1890	1889	1888	1887	1886	1885	1884	1883	1882	1881	1880	1879	1878	1877	1876	1875	1874	1873	1872	1871	1870	1869	1868	1867	1866	1865	1864	1863	1862	1861	1860	1859	1858	1857	1856	1855	1854	1853	1852	1851	1850	1849	1848	1847	1846	1845	1844	1843	1842	1841	1840	1839	1838	1837	1836	1835	1834	1833	1832	1831	1830	1829	1828	1827	1826	1825	1824	1823	1822	1821	1820	1819	1818	1817	1816	1815	1814	1813	1812	1811	1810	1809	1808	1807	1806	1805	1804	1803	1802	1801	1800	1799	1798	1797	1796	1795	1794	1793	1792	1791	1790	1789	1788	1787	1786	1785	1784	1783	1782	1781	1780	1779	1778	1777	1776	1775	1774	1773	1772	1771	1770	1769	1768	1767	1766	1765	1764	1763	1762	1761	1760	1759	1758	1757	1756	1755	1754	1753	1752	1751	1750	1749	1748	1747	1746	1745	1744	1743	1742	1741	1740	1739	1738	1737	1736	1735	1734	1733	1732	1731	1730	1729	1728	1727	1726	1725	1724	1723	1722	1721	1720	1719	1718	1717	1716	1715	1714	1713	1712	1711	1710	1709	1708	1707	1706	1705	1704	1703	1702	1701	1700	1699	1698	1697	1696	1695	1694	1693	1692	1691	1690	1689	1688	1687	1686	1685	1684	1683	1682	1681	1680	1679	1678	1677	1676	1675	1674	1673	1672	1671	1670	1669	1668	1667	1666	1665	1664	1663	1662	1661	1660	1659	1658	1657	1656	1655	1654	1653	1652	1651	1650	1649	1648	1647	1646	1645	1644	1643	1642	1641	1640	1639	1638	1637	1636	1635	1634	1633	1632	1631	1630	1629	1628	1627	1626	1625	1624	1623	1622	1621	1620	1619	1618	1617	1616	1615	1614	1613	1612	1611	1610	1609	1608	1607	1606	1605	1604	1603	1602	1601	1600	1599	1598	1597	1596	1595	1594	1593	1592	1591	1590	1589	1588	1587	1586	1585	1584	1583	1582	1581	1580	1579	1578	1577	1576	1575	1574	1573	1572	1571	1570	1569	1568	1567	1566	1565	1564	1563	1562	1561	1560	1559	1558	1557	1556	1555	1554	1553	1552	1551	1550	1549	1548	1547	1546	1545	1544	1543	1542	1541	1540	1539	1538	1537	1536	1535	1534	1533	1532	1531	1530	1529	1528	1527	1526	1525	1524	1523	1522	1521	1520	1519	1518	1
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---

[illegible][illegible][illegible][illegible][illegible]

cmd
sub
D1

generating a first and second phase signals that are non-overlapping and crossing each other around high points of their signals during every phase cycle from the oscillating signal by a primary phase generator;

generating a third and fourth phase signals that are non-overlapping and crossing each other around low points of their signals during every phase cycle from the oscillating signal by the primary phase generator;

generating a fifth and sixth phase signals from the first and second phase signals, where the fifth and sixth phase signals are similar to the first and second phase signals, and having a predetermined delay from the first and second phase signals by a secondary phase generator;

generating a seventh and eighth phase signals by the primary phase generator;

recharging a first pre-boot capacitor to a first pre-determined level using the first and third phase signals during the first phase;

recharging a second pre-boot capacitor to the first pre-determined level using the second and fourth phase signals during the second phase;

pre-booting a first main pump capacitor to the pre-determined boot level by the second pre-boot capacitor during the first phase;

pre-booting a second main pump capacitor to a pre-determined boot level by the first pre-boot capacitor during the second phase;

recharging the first main pump capacitor to a second pre-determined level by the seventh phase signal during the second phase;

inputting the fifth phase signal to raise the first main pump to a third pre-determined level during the first phase;

outputting the first main pump charge to a V_{ccp} during the first phase;

pre-charging the second main pump capacitor to the second pre-determined level by the eighth phase signal during the first phase;

inputting the sixth phase signal to raise the second main pump to the third pre-determined level during the second phase; and

add
B^b 7

Micron 99-0416